

BOOST-VGA200PS2

KVM Extender, 200meter, VGA, PS2 over RJ45
kabler, AdderLink X-Series X-KVM/P

FEATURES

- KVM extender fra ADDER - senderboks og modtagerboks
- Betjen PC / Server fra 200 meters afstand
- Punk til punkt netværkskabel - UTP
- Opløsning op til 1600 x 1280 pixels
- 5VDC 500mA netadapter
- Tilbud. Begrænset lager!



BOOST-VGA200PS2



SPECIFICATIONS

Driftstemperatur : 0 - 40 °

Forsyning : 5V DC, 2A power supply with an IEC power cable connection.
100-240VAC, Power Frequency: 50-60Hz, Usage: 5VDC at
500mA

LED : The remote and local units are fitted with a link/activity indicator that shows the link status and indicate keyboard and mouse data activity.

Opløsning : 1600 x 1280 at distances up to 100 metres/330 ft, 1024 x 768 at distances up to 200 metres/650 ft.

OS SUPPORT : Compatible with all major operating systems including DOS; OS/2; UNIX; MS Windows 9x, NT, 2000, XP; NetWare and RS6000.

Rækkevidde : Up to 200 m using CATx cable (x: 5,5e,6,7)

Stik : Supports PS/2 style keyboard, PS/2 style mouse, flat-screen and CRT style monitors with standard HD-15 video connectors

