

ETH-FX-FX+25

Multimode to Single Mode 100Mbit Fiber converter
SC connector. Connector 2 different fiber network

FEATURES

- Connect Multimode fiber network with single mode fiber network
- 1 x 100Mbit Single Mode SC
- 1 x 100Mbit Multimode SC
- Wavelength: 1310 / 1310nm
- 100Base-SX / LX fiber network
- 5VDC / 2A adapter included



ETH-FX-FX+25



SPECIFICATIONS

Afstand	:	SC multimode 2 km og 25 km SC singlemode
Dimensioner	:	26 x 70 x 106mm (H x B x D)
Kabel	:	Anvender multimode fiberkabel (50/125 µm eller 62,5/125 µm). Anvender singlemode fiberkabel (9/125 µm)
Omformer	:	Omformer 100 Mbit (SC multimode 1310 nm) til 100 Mbit (SC singlemode 1310 nm)
Stik	:	SC Fiber
Strømforsyning	:	Strømforsynes af medfølgende netadapter 5 volt 2A

